

NEW



diris_791_b_1.cat

Modular multi-function meter

Function

The **DIRIS A10** is a multi-function meter for measuring electrical values in low voltage networks in modular format. It allows all electrical parameters to be displayed and the measurement, energy metering and communication functions to be used. In addition, the **DIRIS A10** has a function for correcting errors in CT connections. It also allow variations in temperature to be detected thanks to its internal temperature measurement function.

Conformity to standards

- IEC 62053-22 class 0,5 S
- IEC 62053-23 class 2
- IEC 61557-12

Applications

Multi measurement

- Current
 - instantaneous: I₁, I₂, I₃, I_n
 - mean maximum: I₁, I₂, I₃, I_n
- Voltages & frequency
 - instantaneous: U₁, U₂, U₃, U₁₂, U₂₃, U₃₁, F
- Power
 - instantaneous: 3P, Σ P, 3Q, Σ Q, 3S, Σ S
 - mean maximum: Σ P, Σ Q, Σ S
- Power factor
 - instantaneous: 3PF, Σ PF

Metering


- Active energy: + kWh
- Reactive energy: + kvarh
- Hours: ☰

Harmonic analysis (level 51)

- Total harmonic distortion
 - Currents: thd I₁, thd I₂, thd I₃
 - Phase-to-neutral voltage: thd U₁, thd U₂, thd U₃
 - Phase to phase voltage: thd U₁₂, thd U₂₃, thd U₃₁

Dual tariff function

Selection of one out of 2 billing tariffs



Events

Alarms on all electrical values

Communications⁽¹⁾


RS485 (JBUS/MODBUS)
digital

Output


- Control of apparatus
- Alarm report
- Pulse report

⁽¹⁾ Available as an option
(see the following pages).

Front panel



Case



Type	Modular
Number of optional modules	4
Dimensions W x H x D	72 x 90 x 64 mm
Case protection index	30
Front protection rating	52
Display type	LCD
Weight	205 g (48250210) - 215 g (48250211)
Voltage and other connection section	4 mm ²
Other connection section	2.5 mm ²

Electrical Characteristics

Current measurement on insulated inputs (TRMS)

CT primary	9 999 A
CT secondary	5 A
Measurement range	0 ... 11 kA
Input consumption	0,6 VA
Measurement updating period	1 s
Accuracy	0.2 %
Sustained overload	6 A
Intermittent overload	10 I _o for 1 s

Voltage measurements (TRMS)

Direct measurement between phases	50 ... 500 VAC
Direct measurement between phase and neutral	28 ... 289 VAC
Input consumption	≤ 0,1 VA
Measurement updating period	1 s
Accuracy	0.2 %
Sustained overload	800 VAC

Power measurement

Measurement updating period	1 s
Accuracy	0.5 %

Power factor measurement

Measurement updating period	1 s
Accuracy	0.5 %

Frequency measurement

Measurement range	45 ... 65 Hz
Measurement updating period	1 s
Accuracy	0.1 %

Energy accuracy

Active (according to IEC 62053-22)	class 0.5 S
Reactive (according to IEC 62053-23)	class 2

Auxiliary power supply

Alternating voltage	200 ... 277 VAC
AC tolerance	± 15 %
Frequency	50 / 60 Hz
Consumption	< 3 VA

Outputs (Pulse)

Number	1
Type	100 VDC - 0.5 A - 10 VA
Max. number of operations	≤ 10 ⁸

Communication

Link	RS485
Type	2 ... 3 half duplex wires
Protocol	JBUS/MODBUS® in RTU mode
JBUS/MODBUS® speed	1400 ... 38400 bauds

Operating conditions

Operating temperature	- 10 ... + 55°C °C
Storage temperature	- 20 ... + 70°C °C
Relative humidity	85 %


Connection

Low voltage balanced network


Recommendation:

- For IT earthing systems, it is recommended that the CT secondaries are not connected to the earth.
- While disconnecting the DIRIS, the secondaries of each current transformer must be short-circuited. This operation can be carried out automatically from a product in the SOCOMEC catalogue, PTI: Please consult us.
- It is recommended that the earthing point for the DIRIS A10 and the current transformer secondaries must not be earthed at the same time.


3/4 wires with 1 CT



Single phase




Two phase




Connection - Low voltage unbalanced network


3/4 wires with 3 CTs



3 wires with 2 CTs



3 wires with 2 CTs




Use of 2 CTs reduces by 0.5 % the accuracy of the phase, whose current is worked out by vector calculation.

Use of 2 CTs reduces by 0.5 % the accuracy of the phase, whose current is worked out by vector calculation.


Other information

Communication via RS485 link

AC & DC auxiliary power supply




diris.820.a.1.x.cat




It is recommended that the auxiliary power supply must be protected by the use of 500 mA gG fuses.


⌚ Terminals




Communication module



Output or alarm module



Input module



⌚ References



Switches

Description

DIRIS A10 (grey colour available on request)	4825 0010
DIRIS A10 with JBUS/MODBUS communication via RS485 (grey colour available on request)	4825 0011

DIRIS A10 Reference

4825 0010
4825 0011

Description of accessories

Description of accessories	Pack qty	Reference
Fuse combination switches for the protection of voltage inputs (type RM) 3 poles	4	5601 0018
Fuse combination switches for the protection of the auxiliary supply (type RM) 1 pole + neutral	6	5601 0017
Fuses type gG 10x38 0.5 A	10	6012 0000
Current transformers range		See page XXX